- 1.執行 FlashCMD 前,請先將所有執行中的程式關閉
- 2.將 BIOS copy 到 FlashCMD 資料夾中

📙   🛃 📕 🖛   FlashCM	D9.02_64bit_B17052601			- 0	$\times$			
File Home Share	View				~ 🔞			
← → × ↑ 🚺 > Fl	ashCMD9.02_64bit_B17052601 v ඊ			Search FlashCMD9.02_64bit_B , P				
	Name	Date modified	d	Туре	Size			
🖈 Quick access		5/26/2017 4/2	2 DM	Application extens	2.2			
Desktop 🖈	Elach dll	5/26/2017 4/2	2 PM	Application extens	2.2			
👆 Downloads 🛛 🖈	ElashCMD 64	5/26/2017 4:2	6 PM	Application	21			
🗄 Documents 🖈	msvcr100.dll	msvcr100.dll 2/18/2011 11:52 P			8			
Pictures 🖈	Q170MMK.F22	5/25/2017 5:5	1 PM	F22 File	16.3			
FlashCMD9.02 6 #	ReadMe	5/26/2017 4:3	4 PM	Text Document				
FlashCMD9.02_64bi	VccDrv.dll	3/29/2012 2:3	MA 8	Application extens				
Music								
Videos								
ConeDrive								
This PC								
Network								
	<				>			
7 items					8:: -			

3.使用 Windows "搜尋" 中輸入 cmd

4.搜尋到" Command Prompt",用滑鼠按右鍵選擇" Run as administrator"

	) <b>(</b>	Filters 🗸				
⊚ 4 <sup>est matcl</sup>	n					
Command Promp		pt				
De	sktop app	Run as administrator	-			
Q cmd	- Search the web	Open file location				
y- und seatch die web		Pin to Start				
3						
, Cmd			0	е	-	Ŷ

5.在 Command Prompt 下指令"cd" 至 flashcmd 資料夾

C:\windows\system32> cd "flashcmd 資料夾的路徑"

6.輸入 flashcmd\_64.exe /d Q170MMK.F22 (不同 model 輸入相對應的檔名,可 參考 FlashCMD 目錄 readme.txt )



7.燒錄後系統會自行重開機